


SPECIFICATION

- Light Source LED Module (Mounted)
- Cone White Cone(WC), Matte black Cone(MC), Chrome Cone(CC)
- Light Distribution Wide(W)
- Frame White(SWF), Matte black(SMF)
- Dimming method 0-10V
- Input Voltage 220V±6%, 240V±6%(Dedicated driver input voltage)
- Input current 0.148A(Dedicated driver input voltage, 220V input)
0.136A(Dedicated driver input voltage, 240V input)
- Power Consumption 29.3W(Included dedicated driver, 220V input)
29.4W(Included dedicated driver, 240V input)
- ※The power consumption is measured based on the measuring method, JIS C 8105-3.
- Dedicated Driver Constant current (50/60Hz shared)
- Fixture Input voltage 36.8V
- Fixture Input current 0.7A
- Dimming signal input current 2mA
- Weight 630g(Includes dedicated driver)
- Safety Wire is attached

PRODUCT CODE



- MMP-080F/WC/SWF/W/20B27/Z2/3
MMP-080F/WC/SWF/W/20B30/Z2/3
MMP-080F/WC/SWF/W/20B35/Z2/3
MMP-080F/WC/SWF/W/20B40/Z2/3
- MMP-080F/MC/SWF·SMF/W/20B27/Z2/3
MMP-080F/MC/SWF·SMF/W/20B30/Z2/3
MMP-080F/MC/SWF·SMF/W/20B35/Z2/3
MMP-080F/MC/SWF·SMF/W/20B40/Z2/3
- MMP-080F/CC/SWF·SMF/W/20B27/Z2/3
MMP-080F/CC/SWF·SMF/W/20B30/Z2/3
MMP-080F/CC/SWF·SMF/W/20B35/Z2/3
MMP-080F/CC/SWF·SMF/W/20B40/Z2/3



	PARTS	MATERIAL	REMARK
1	Socket Holder	ADC	Acrylic Baking Finish
2	LED Module		
3	Reflector	Aluminum	
4	Body	ADC	Acrylic Baking Finish
5	Glare Cut Ring	Silicon	
6	Cone	ADC	WC,MC: Acrylic Baking Finish CC:Plating Finish
7	Unit Mounting Spring	Stainless Steel	
8	Mounting Frame	ADC	Acrylic Baking Finish
9	Safety Wire	Stainless Steel	
10	Safety Connector	Resin	
11	Dedicated Driver		0-10V control dimming system

ATTENTION

- Do not cover the fixture with the heat insulator etc.
- Please use constant current driver.
- There is no sending terminal block on the dedicated driver (primary side).
- Connect input-side power wire to the approved driver directly.
- Danger! Do not remodel the fixture.
- Use within 0℃~35℃ ambient temperature range
- Connect a safety wire to the fixture and mounting frame directly.
- Emission color and brightness would be different even within the same model.
- Do not use a radio or TV near the fixture. The unit may generate noise in the radio or TV.
- Use 0-10V control dimming system (SR-2830AS-1-10V(Sold separately)) only
- Calculate the capacity in accordance with JIS C8155 standard.
- Keep distance of the fixture and objects 0.2m or more.
- The height of inside the ceiling have to be 150mm or more to install the driver there.



- When mounting the fixture, please align the positions of notches of the cone and the mounting frame
- To remove the fixture, push the flat head screwdriver (size: 5.5 x 75) into the notch.
- This fixture is ceiling installation only. It can not be mounted on an inclined ceiling or wall.