

SERIES


ModuleX®80

FUNCTION

Adjustable downlight

CAT. No.

MSP-080A/SWF・SMF/W/12B/DL/3




SPECIFICATION

- Light Source LED Module (Mounted)
- Light Distribution W-Wide
- Mounting Frame White(SWF)・Matte Black(SMF)
- Cone Color White Cone(WC)
Matte Black Cone(MC)
Chrome Cone(CC)
- Dedicated Driver Constant current (50/60Hz shared)
- Fixture Input Voltage 36. 9V
- Fixture Input Current 0. 48A (0. 5A MAX)
- Weight 390g
- Attached Safety Wire

PRODUCT CODE

- MSP-080A/WC/SWF/W/12B27/DL/3
- MSP-080A/WC/SWF/W/12B30/DL/3
- MSP-080A/WC/SWF/W/12B35/DL/3
- MSP-080A/WC/SWF/W/12B40/DL/3
- MSP-080A/MC/SWF・SMF/W/12B27/DL/3
- MSP-080A/MC/SWF・SMF/W/12B30/DL/3
- MSP-080A/MC/SWF・SMF/W/12B35/DL/3
- MSP-080A/MC/SWF・SMF/W/12B40/DL/3
- MSP-080A/CC/SWF・SMF/W/12B27/DL/3
- MSP-080A/CC/SWF・SMF/W/12B30/DL/3
- MSP-080A/CC/SWF・SMF/W/12B35/DL/3
- MSP-080A/CC/SWF・SMF/W/12B40/DL/3

[mm]



	PARTS	MATERIAL	REMARK
1	Body	ADC	Acrylic Baking Finish
2	LED Module		
3	Reflector	Aluminum	
4	Filter	Resin	
5	Hood	ADC	Acrylic Baking Finish
6	Cone	ADC	Acrylic Baking Finish(WC・MC) Plating Finish(CC)
7	Mounting Frame	ADC	Acrylic Baking Finish
8	Unit Mounting Spring	Stainless Steel	
9	Safety Wire	Stainless Steel	
10	Safety Connector	Resin	

ATTENTION

- Use within 0℃~35℃ ambient temperature range
- Do not cover fixtures with the heat insulator etc.
- Keep distance of the fixtures and objects 0. 2m or more.
- Danger ! Do not remodel fixtures.
- Connect a safety wire to the fixture and mounting frame directly.
- Emission color and brightness would be different even within the same model.
- Please use constant current driver.
- Connect input-side power wire to the Approved driver directly.
- Please do not remove safety connector
- Please do not plug in the wrong electrode to the applicable driver.
It may cause shortening of LED lifetime or the damage to the LED component.
- This equipment is a ceiling installation exclusive equipment. It can not be mounted on an inclined ceiling or wall.
- Please use the 'class2' driver.
In that case, grounding is not required.

ModuleX

ModuleX Inc.

SPECIFICATION SHEET

SCALE

1 / 2

CREATED DATE

1/APR/2020

REVISION DATE